


DT105X / PB105 Series



Cash Drawer Trigger & Printer Beeper User's Manual

Contents

| | |
|---|----|
| Information | 1 |
| Technical And Operational Description | 3 |
| Connections | 5 |
| Load Test | 7 |
| Specifications | 8 |
| Communication Protocol | 9 |
| Application Note | 10 |

FCC COMPLIANCE STATEMENT

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communication.

Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

GIGA-TMS Inc.

Office : 8F No 31 Lane 169, Kang-Ning St., Hsi-Chih, Taipei, Taiwan

Tel : 886-2-2695-4214

































Fax : 886-2-2695-4213

Web site : <http://www.gigatms.com.tw>

E-mail : promag@ms24.hinet.net


Information

Cash Drawer Trigger & Printer Beeper


| MACHINE TYPE | FUNCTION |
|---|---|
|  <p>DT105U Cash Drawer Trigger USB Interface Command control and RTS/DTR signal control</p> | <div>     </div> <div>     </div> <div>    </div> |
|  <p>DT105R Cash Drawer Trigger RS232 Interface Command control and RTS/DTR signal control</p> | <div>     </div> <div>     </div> <div>     </div> |
|  <p>PB105 Printer Beeper</p> | <div>     </div> <div>   </div> |

■ Standard Package


DT105U



Main unit
(DT105U)




Velcro Fastener
(ASY-M93-1049-46)




CD-ROM
(DISK5140)


DT105R




Main unit
(DT105R)



Velcro Fastener
(ASY-M93-1049-46)




Power Plug
(ASY-M93-6022-1)




CD-ROM
(DISK5140)

PB105




Main unit
(PB105)



Velcro Fastener
(ASY-M93-1049-46)


■ Optional



Power Adaptor
DC9V/120VAC (APR-1025) or DC9V/230VAC (APR-1013)

Technical And Operational Description

■ Front Panel and Operations



- **DRIVE INDICATOR (Red color)**
The status LED provides visual indication of the device output operating
- **READY/ RECEIVE INDICATOR (Green color) <DT105X>**
Indicating the device is ready to accept new inputs and communication status from Host.
- **BUZZER HOLE < PB105 >**
The sound's hole for Buzzer.
- **PHONE JACK**
For connection to Cash Drawer .
- **CABLE**
Connect to USB or RS232 (include power supply) interface.

■ Introduction

This manual provides basic information about the Models of DT105U (DT105R) Universal Serial Bus (RS232 Serial Port) Cash Drawer Triggers, and the PB105 Printer Beeper.

The DT105U(DT105R) Cash Drawer Trigger is designed to provide USB (RS232) interfacing to the cash drawer. This allows cash drawers, previously connected to POS printers and cash registers, to be connected to a USB (RS232) port of the computer.

The DT105U USB Trigger uses a Virtual Serial Port Driver, making it appear to have the software like a standard RS232 Serial Port. This way the existing POS Software can communicate with the USB Cash Drawer Trigger as if it were connected to a Serial Port. A unique serial number is assigned to each USB Trigger Module and the Driver Software will assign the next available Serial Port to each device it recognises (multiple Triggers can be used on one PC).

The DT105U(DT105R) module is designed to accept modular cash drawer connectors. All standard POS printer drawer open commands are used to trigger the device and the ESC/POS status command is also available to read the drawers open or closed condition.

- * **DT105U** is to open the cash drawer when it receives the trigger command or the RTS/DTR signal control from the computer via USB port.
- * **DT105R** is to open the cash drawer when it receives the trigger command or the RTS/DTR signal control from the computer via RS232 port.

■ Indicators Information

DT105X with COMMAND control

| STATUS | GREEN LED | RED LED | BUZZER | COMMUNICATION |
|------------------|---------------|---------------|-----------|---------------|
| POWER ON | BLINK 2 TIMES | BLINK 2 TIMES | BEEP-BEEP | X |
| READY | ON | OFF | X | O |
| OPEN CASH DRAWER | OFF | ON | BEEP | X |
| COMMUNICATION | BLINK | OFF | X | X |

DT105X with RTS/DTR signal control


| STATUS | GREEN LED | RED LED | BUZZER | RTS/DTR |
|------------------|---------------|---------------|-----------|-----------|
| POWER ON | BLINK 2 TIMES | BLINK 2 TIMES | BEEP-BEEP | X |
| READY | ON | OFF | X | H/L |
| X | OFF | OFF | X | L/L , H/H |
| OPEN CASH DRAWER | OFF | ON | BEEP | L/H |

PB105

| STATUS | GREEN LED | BUZZER |
|--------|-----------|--------|
| READY | OFF | X |
| ACTION | ON | BEEP |


Connections

WAS-1510



| USB | COLOR | FUNCTION | 5 PIN |
|-------|------------|----------|-------|
| 1 | RED | POWER + | 5 |
| 2 | WHITE | D - | 4 |
| 3 | GREEN | D + | 3 |
| 4 | BLACK | GND | 2 |
| Shell | Drain Wire | Shield | 1 |

WAS-1526




| DSB 9P FEMALE * | COLOR | FUNCTION | 7 PIN |
|-------------------|--------|------------|-------|
| 3 | PURPLE | TXD | 5 |
| 2 | WHITE | RXD | 6 |
| 4 | YELLOW | DTR | 2 |
| 5 | BLACK | GND | 4 |
| 7 | BLACK | RTS | 1 |
| 8 | BLUE | CTS | 3 |
| POWER JACK | | | |
| + | RED | 9-12Vdc ** | 7 |
| - | BLACK | GND | 4 |

* DSB 9P FEMALE Pin 6,7 connected together


** 5Vdc to customer specifications

WAS-1528




| 6P6C | COLOR | FUNCTION | 6 PIN |
|------|--------|----------|-------|
| 1 | BLACK | GND | 1 |
| 2 | WHITE | Sol - | 2 |
| 3 | RED | Status | 3 |
| 4 | YELLOW | Sol + | 4 |
| 5 | PURPLE | Sol - | 5 |
| 6 | BLUE | GND | 6 |

■ 6P6C Modular Jack Connector




| Pin Number | Function |
|------------|----------------------------|
| 6 | GND |
| 5 | Sol - (for EPSON drawer 2) |
| 4 | Sol + |
| 3 | Status |
| 2 | Sol - |
| 1 | GND |

■ Application Note




Load Test


Load Test Circuit



Load Test Timing Diagram



Specifications



USB Interface (for DT105U)

USB V1.1 & USB HID Class V1.0

RTS (Request To Send) & DTR (Data Terminal Ready) be used



RS232 Interface (for DT105R)


RS232 , Half-Duplex , 8N1 , 9600 bps

RTS (Request To Send) & DTR (Data Terminal Ready) be used



Output Power

RJ12 Connector , Rating suits 10 - 36 Ohms solenoid (24Volts @1Amp), On time : 150ms, Repeat rate : 3 seconds



MULT-COLOR LED Display


Green LED - Ready / Communication

Red LED - Open Cash Drawer



Operate Sound (for DT105U, DT105R)

3Khz , 45 dB , Built in the device




Operate Sound (for PB105)

3Khz , Min 105 dB at 30cm / 24 Volts



Power Supply (for DT105R)

DC 9V -12V , 500mA (DC 5V to customer specifications)



Dimensions

D 26 x W 56 x H 85 mm

Cable Length - DT105U : 1650 mm

DT105R,DT232,BP105 : 1550 mm




Weight

DT105U : 90g (including cable)

DT105R : 110g (including cable)

BP105 : 70g (including cable)




Environment :

Operating Temp : 0 ~ 55 Deg.C

Storage Temp : -10 ~ 55 Deg.C

Humidity : 10 ~ 90 % relative



Mounting :

Portable or Any surface

Communication Protocol

DT105U & DT105R Communication Protocol


Any baudrate communication can active DT105 to open cash drawer.

DT105U & DT105R Signal Control and Status


| CONTROL | PIN4 DTR RS232/TTL | PIN7 RTS RS232 / TTL | RED LED | GREEN LED | BUZZER LED | STATUS |
|---------|-----------------------|-------------------------|------------|--------------|---------------|--------|
| | +12V / L | +12V / L | OFF | OFF | OFF | X |
| | +12V / L | -12V / H | OFF | ON | OFF | READY |
| | -12V / H | +12V / L | ON | OFF | ON | OPEN |
| | -12V / H | -12V / H | OFF | OFF | OFF | X |
| STATUS | PIN8 CTS RS232/TTL | STATUS | | | | |
| | +12V / L | Cash drawer open | | | | |
| | -12V / H | Cash drawer close | | | | |

Application Note


1. POS System For Standard Connect




2. POS System For Standard Connect Plus PB105



3. POS System Replace POS Printer By DT-105U/R



4. POS System Replace POS Printer By DT-105U/R Plus PB105



5. POS System Replace POS Printer By DT-105U/R Plus Two PB105

